



Access Controller Metal Power Supply

Be applied to building talk backs and kinds of access controllers

Functions

Implicit 6 column cells

- * With NC outputs, it can be used for all kinds of electric lockers.
- * It has time prolongation control circuit, unlock duration adjusting button with time range 0-10s.
- * It is deployed with unlock button that can unlock directly.
- * It has auto protection, fuse and power switch.
- * Optional built-in 12V 7AH rechargeable battery.
- * Adjustable output voltage at range 11-14V.
- * It gives stable voltage output, which provides stable work condition for electronic.

Don't implicative and implicit battery position 4 column

- * Dual+12 V output
- * It has auto protection, built-in fuse
- * But the outer batteries.



Model	PS-12V-110V
AC Input Voltage	AC110V
Output Voltage	DC12V
Output Electric Current	5A
Output Power	60W
Operating Temperature	20C~+60C
Operating Humidity	≤90%RH
Time	0-10s
Dimension	273*228*65mm
Weight	4KG



Definition of output terminals

Don't implicit batteries

